

# KT-300 Door Controller

## INNOVATIVE AND POWERFUL

- Update Firmware Directly from System Workstation
- Fast! Up to 115,200 Bauds
- Ready to Go! No Dip Switches or Jumpers to Set!
- 5V and 12V Reader Power
- Input and Output Expansion Modules

### Trouble and Reporting

The KT-300 constantly supervises battery conditions and reports “Low battery” or “No battery” status to the system. All power outputs are individually protected against short circuits and surges, by a self-resetting PTC. Locking devices are also supervised for short and open circuits.

### Built-In Combus Expansion

The KT-300 supports expansion modules to add inputs, outputs and an LCD time display for Time and Attendance functions.



# KT-300 Door Controller

INNOVATIVE AND POWERFUL

The KT-300 is designed to meet the highest standards of access control and point monitoring applications.

The KT-300 controls 2 doors and is easily linked to a network controlling thousands of doors.





### Ordering Information

<b>KT-300/128k</b>	Door controller with 128k memory including KT-300CAB, KT-300ACC and KT-300LOCK
<b>KT-300/512k</b>	Door controller with 512k memory including KT-300CAB, KT-300ACC and KT-300LOCK
<b>KT-300PCB/128k</b>	KT-300/128k PCB only and accessory kit KT-300ACC
<b>KT-300PCB/512k</b>	KT-300/512k PCB only and accessory kit KT-300ACC
<b>KT-300ACC</b>	Accessory kit including: 2x1.0K ohms, 10x5.6K ohms, 2x120 ohms, PCB standoff, lock hole cover, ground wire and screwdriver
<b>KT-PC4108</b>	8-zone input expansion module for KT-300
<b>KT-PC4204</b>	4-relay and COMBUS additional power supply module for KT-300
<b>KT-PC4216</b>	16-output expansion module for KT-300
<b>KT-RM1</b>	External isolation relay SPDT for KT-300 output (RL1/RL2)
<b>KT3-LCD</b>	LCD time & date display for KT-300, used for Time and Attendance
<b>KT-300CAB</b>	KT-300 black metal cabinet including KT-300LOCK
<b>KT-4051CAB</b>	Standard black metal cabinet for KT-PCxxxx modules (order keylock separately) 16-13/16" H x 10-3/8" W x 4-1/8" D (42.7cm x 26.4cm x 14.4cm) EMT 3/4" (1.9cm)
<b>KT-300LOCK</b>	Keylock for KT-300CAB and KT-4051CAB metal cabinet (2 keys / same as KT-200)
<b>KT-300TAMP</b>	Tamper switch for KT-300CAB and KT-4051CAB metal cabinet
<b>TR1637W/CSA</b>	AC Transformer, Wire-In, 110V/16V (37VA) CSA
<b>TR1640P/CSA</b>	AC Transformer, Plug-In, 110V/16V (40VA) CSA
<b>TR1640P/UL</b>	AC Transformer, Plug-In, 110V/16V (40VA) UL
<b>TR1640W-220</b>	AC Transformer, Wire-In, 220V/16V (40VA) CE
<b>USB-485</b>	USB to RS-485 communication interface
<b>VC-485</b>	RS-232 TO RS-485 communication interface

### KT-300 Technical Specifications

<b>Input power</b>	16VAC, 40VA, class 2 transformer
<b>Battery backup</b>	1 battery 12V, 7AH, supervised, provides operation for up to 12 hours
<b>Dimensions (H-W-D) inches</b>	11-3/4" H x 11-3/8" W x 3" D (29.9cm x 28.8cm x 7.7cm) EMT 3/4" (1.9cm)
<b>Weight (with metal cabinet)</b>	5.4 lbs. (2.4 kg)
<b>Operating temperatures</b>	From 35°F to 110°F (2°C to 40°C)
<b>Reader types</b>	Wiegand, proximity, bar code, magnetic, integrated keypad and others
<b>Monitored points (inputs)</b>	8 monitored points, NO/NC, with or without end-of-line resistors (expandable to 16)
<b>Points maximum wiring</b>	2,000' (600 meters) – (AWG #22)
<b>Door strike power</b>	12VDC, 250mA each, supervised
<b>Auxiliary outputs (LED, BUZ)</b>	4 outputs, 25mA max. each Open collector
<b>Control relay outputs (R1, R2)</b>	2 control relay outputs, 12VDC, 25mA totals each, Open collector (Optional relay RM1 available)
<b>Auxiliary power output</b>	12VDC @125mA max., protected and supervised
<b>Reader power outputs</b>	12VDC and 5VDC @125mA total, protected and supervised
<b>Communication ports</b>	RS232, RS485 and COMBUS
<b>Communication speed</b>	Up to 115,200 bps (automatic detection)
<b>Firmware Flash memory</b>	128k
<b>RAM memory</b>	128k (512k unit available). Protected by a lithium battery
<b>Network autonomy</b>	Distributed data and processing
<b>Certifications</b>	UL294, CE, FCC

### Expansion Modules Specifications

<b>KT-PC4204</b>		4-relay and COMBUS additional power supply module. Current draw: 30mA (from Combus). 40VA 16-18V AC transformer required, maximum 12V 7Ah battery required. Four programmable relay form C contacts rated 2A. Tamper contact input. (UL, CE, FCC)
<b>KT-PC4216</b>		16-output module. Current draw:15mA (from Combus). Output 12VDC, 50mA max. each, power drawn from Combus. Tamper contact input. (UL, CE, FCC)
<b>KT-PC4108</b>		8-zone input module. Current draw 30mA (from Combus). Aux. power 12VDC, 250mA max., drawn from Combus. Tamper contact input. (UL, CE, FCC)
<b>KT3-LCD</b>		LCD time/date display for Time and Attendance. Current draw: 50mA (from Combus). (UL, CE, FCC)

